

**SECO-LARM®**



PR-112S-A

## **Stand-Alone Proximity Card Reader**

## Description

---

The new **ENFORCER** Proximity Reader provides an inexpensive, flexible solution for controlled access. The unit combines simple installation, quick programming, and high reliability.

- Stand-alone Proximity Card Reader
- Use in small businesses, homes, gates/parking structures, apartments and other locations
- Sealed and waterproof (IP67). Mounts easily to interior and exterior wall
- Attractive tri-color wave shaped LEDs status bar indicates proximity reader's mode and status
  - **Blue** – On/Valid Card Indicator
  - **Green** – Programming Mode
  - **Red** – Invalid Card
- Output relay for either time (1 to 180 seconds) or "Toggle" mode
- Egress input to exit the protected area without using the proximity reader
- Buzzer is programmable for audible confirmation or silent mode
- Up to 100 user cards can be programmed
- User cards easily deleted. Delete a single card, or all cards
- Up to 5 "Master" cards can be programmed
- 10 Cards included
- Optional accessories:
  - PR-K1S1-A:** Additional proximity cards, sold in packs of ten
  - PR-K1K1-AQ:** Proximity tags, sold in packs of ten

## Specifications

---

Operating Voltage	12VDC
Current Draw- Active	200mA @ 12VDC
Current Draw- Standby	80mA @ 12VDC
Transmit Frequency	125kHz
User Card Read Range	6" (15cm)
Master Card Limit	5 cards
User Card Limit	100 Cards
Output	1 Relay (NO/NC/COM)
Contact Rating	1A@30V
Relay Time Delay	1~180 s / Toggle Mode
Operating Temperature	-4°~158° F (-20°~70° C)
IP Rating	Waterproof IP67
Dimensions	3-11/16"x1-3/4"x5/8" (95x44x17 mm)